



D9412GV3 Control Panel



The D9412GV3 Control Panel delivers a powerful new solution for intrusion, access control, and fire alarm system applications. The control panel includes a communicator that sends events to selected public switched telephone network (PSTN), IP network, or general packet radio service (GPRS) destinations through four programmable route groups. The control panel provides up to 246 individually identified points. Each point:

- Accommodates normally-open (NO) and normally-closed (NC) devices with end-of-line (EOL) resistor supervision
- Is programmable for fire, fire supervisory, or intrusion applications.

With the D9412GV3 you can:

- Monitor alarm points for intruder or fire alarms while operating user keypads and other outputs
- Program all system functions locally or remotely (attended or unattended) through Remote Programming Software (RPS); program critical parameters on-site through a keypad.
- Add up to eight doors of access control using the optional D9210BLC Access Control Interface Module.

Functions

Programmable Outputs

- 2 A alarm power at 12 VDC
- 1.4 A auxiliary power at 12 VDC

- ▶ Fully integrated intrusion, fire, and access control allows users to interface with one system instead of three
- ▶ Conetix IP-based communication options provide high-speed, secure alarm transport and control through connection of up to two wired (DX4020) and/or wireless (ITS-DX4020-G) network interfaces
- ▶ Up to 32 programmable areas with perimeter and interior partitioning
- ▶ 246 points with flexible configuration options to meet multiple installation requirements
- ▶ Commercial Wireless allows up to 238 RF points
- ▶ Up to 16 supervised keypads (vacuum fluorescent, ATM style, or touch-screen keypads available)

- Four alarm-output patterns
- Programmable bell test

System Response

- High-performance micro-controller provides industry-leading system response
- 31 custom point indexes, including fire supervisory
- Selectable point response time
- Cross point capability
- Fire alarm verification
- Fire inspector's local test
- Watch mode
- Scheduled events (skeds) arm, disarm, bypass and unbypass points, control relays, control authority levels, and control door access

User Interface

- Supervision of up to 16 keypads (up to 32 unsupervised keypads can be used)
- Custom keypad text is fully programmable, including remote programming
- Full function command menu including custom functions
- Authority by area and 16-character name for each user
- 14 custom authority levels control user's authority to change, add, or delete passcodes or access control credentials; to disarm or bypass points; and to start system tests

Area Configurations

Area programming offers a wide selection of different system configurations. Each area is assigned an account number to define annunciation, control, and reporting functions. Multiple areas can be linked to a shared area which is automatically controlled (hallway or lobby). Area arming can be conditional on other areas (master or associate). Any area can be configured for perimeter and interior arming, not requiring a separate area for this function.

Two Man Rule

Two Man Rule provides added security by requiring:

- Two people present at opening
- Two unique passcodes on the same keypad to disarm an area

Without the second passcode, the system denies entry.

Early Ambush

Early Ambush requires two passcode entries on the same keypad. Enter the same passcode twice or have two unique passcodes, depending on the configuration. The first entry disarms the area and the second entry stops a timer programmed to send a duress event. If the second entry does not occur within the programmed time, the system generates a duress event. Early Ambush allows users to inspect the premises and use the system to confirm that the area is safe to enter, providing added security.

Easy Exit Control

The D9412GV3 Control Panel changes from one armed state to another armed state without disarming. For example, if you change the state from Master Arm to Perimeter Arm, the control panel complies and reports the change. Easy Exit Control reduces the number of keystrokes, simplifying system operation.

Programmable Passcode-controlled Menu List

The system prompts users to enter a passcode prior to viewing the keypad menu. The keypad display shows the user the menu options allowed according to the user's authority level. Passcode-controlled menus provide users only with the options and information pertinent to them, simplifying system operation.

Passcode Follows Scope

Use Passcode Follows Scope to restrict passcode arming and disarming to the keypad's immediate local area, even if the keypad can report events from other areas. Passcode Follows Scope simplifies the arming and disarming procedure without limiting any other keypad capabilities.

Invisible Walk Test

A menu item allows the user to test invisible 24-hour points within the scope of the keypad without sending a report to the central station.

Door-Activated Custom Function

A custom function activates when user credentials are presented to a D9210B door controller's reader. The custom function behaves as though the user performed a function at the keypad associated with the door controller.

Passcodes

User passcodes contain three to six digits. Assign each user one of 14 customized authority levels in each area. Restrict passcodes to operate only during certain times.

The Two Man Rule and Early Ambush options require two passcodes, providing additional security in financial establishments such as banks.

Communications

The D9412GV3 Control Panel prioritizes and sends reports in Contact ID or Modem IIIa² communications formats to four route groups. Each group has a programmable primary and backup destination.

The D9412GV3 provides flexible communications for most central stations with reporting capabilities such as:

- Individual point numbers
- Opening or closing reports by user and area number
- Remote programming attempts
- Diagnostic reports

The D9412GV3 uses the DX4020 Ethernet Network Interface Module and/or the ITS-DX4020-G GPRS/GSM Communicator to communicate with the Conettix D6600 and D6100i Communications Receiver/Gateways. Using Conettix IP communication offers a secure path that includes anti-replay/anti-substitution features and provides enhanced security with encryption. Both the DX4020 and ITS-DX4020-G can be used for remote programming.

Security and Fire Detection

The D9412GV3 Control Panel provides eight on-board points, and up to 238 additional off-board points (depending on model and expansion interfaces). You can program individual points to monitor all types of burglar alarms, fire alarms, and supervision devices.

Commercial Wireless

The Commercial Wireless platform, powered by Inovonics wireless mesh network technology, ensures superior range, reliability, and scalability for commercial applications. Using a wide range of transmitters and repeaters, this proven technology provides flexibility and performance to meet the most stringent requirements. This exclusive protocol is available only on Commercial Wireless products.

The Commercial Wireless platform sends redundant information on several multi-frequency channels within the FCC Part 15 900 MHz band, providing superior range and reliability. In comparison, systems that use a single frequency technology can only send information on one narrow band channel. Any interference within the band can cause missed signals. With wireless registration, it is easy to add this technology to any application.

Event Log

The event log stores up to 1,000 local and transmitted events. The event log includes time, date, event, area, point, and user number. View the event log from a keypad or use RPS to remotely retrieve event information. RPS operators can retrieve events periodically using one phone call, rather than receiving several calls each day. When the event log reaches a programmed threshold of stored events, it can send an optional report to a receiver.

Access Control

The D9412GV3 provides custom door strike, point shunt and auto disarming response by area. There are 14 panel-wide access levels with both manual and scheduled control.

Store, view, or print access events such as:

- Access granted
- No entry
- Request-to-enter
- Request-to-exit

Scheduled Events (Skeds)

The internal clock and calendar start individually scheduled events (skeds). Skeds perform functions such as arm or disarm, relay control, or point bypassing. The D9412GV3 Control Panel offers:

- 40 scheduled events with up to 25 different functions
- Eight opening windows and eight closing windows
- Eight user windows
- Day-of-week, date-of-month, or holiday only schedules
- Four holiday schedules of 366 days each (leap year)

Fire Test

When a user activates Fire Test Mode, the control panel suppresses all reports to the central station. The keypad and annunciator show all testing data. An automatic sensor reset feature saves time; you do not need to reset the sensors manually. At the end of test, the keypad shows the number of untested points.

Programming, Diagnostics and Controls

Installers can do limited programming on-site with a keypad (critical parameters; such as, .Account IDs, Central Station and RPS IP addresses and phone numbers, reporting formats, and such). They can also do full programming on-site or remotely (attended or unattended) with RPS. A programmable system passcode prevents unauthorized remote programming.

D9412GV3 Control Panels accommodate up to four separate destinations for primary, alternate, and backup receivers for automatic test reports.

When resetting alarms or arming or disarming a system, the user is identified by name and number.

ROM Updates

An on-site flash update key provides for easy feature enhancements without replacing ROM chips.

Certifications and Approvals

Region	Certification	
USA	UL	AMCX: Central Station Alarm Units (ANSI/UL 1610 and 1635); AMTB: Control Panels, SIA False Alarm Reduction (UL 864 and ANSI/SIA CP-01-2000); AOTX: Local Alarm Units (ANSI/UL 609 and ANSI/UL 464); APAW: Police Station Alarm Units (ANSI/UL 365 and ANSI/UL 464); APOU: Proprietary Alarm Units (ANSI/UL 1076); NBSX: Household Burglar Alarm System Units (ANSI/UL 1023); UOJZ: Control Units, System (ANSI/UL 864); UTOU: Control Units and Accessories, Household System Type (ANSI/UL 985)
	FM	
	CSFM	7165-1615:0238 FIRE ALARM CONTROL UNIT (COMMERCIAL) 7167-1615:0239 CONTROL UNIT (HOUSEHOLD)
	FDNY-CoA	6059
	FCC	Designed to comply with Part 15

Installation/Configuration Notes

Compatible Products

Keypads

D1260 Series Keypads
(D1260, D1260W, D1260R, D1260BLK, D1260B)

D720 Series Keypads
(D720, D720W, D720R, D720B)

D1255 Series Keypads
(D1255, D1255W, D1255B, D1255RB)

D1256RB Fire Keypad

D1257RB Remote Fire Alarm Annunciator

D1265 Touch Screen Keypad

D279A Independent Zone Control

Detectors

D278S Four-wire Addressable Detector Base, 12 VDC
 D285/TH Photoelectric Smoke Detector Heads
 D298S Addressable Detector Base, 24 VDC
 D7050 Series Addressable Photoelectric Smoke and Smoke Heat Detector Heads
 F220-B6PM/S Addressable Detector Bases with POPITs
 MX775i Addressable PIR Detector
 MX794i Long Range Multiplex PIR Detector
 MX934i Addressable PIR Detector
 MX938i Addressable PIR Detector
 ZX776Z PIR Detector
 ZX794Z Long Range PIR Detector
 ZX835 TriTech Microwave/PIR Detector
 ZX935Z PIR Detector
 ZX938Z PIR Detector
 ZX970 PIR/Microwave Detector
 Bosch conventional detectors, including Blue Line, seismic, PIR, TriTech PIR Microwave, photoelectric, heat, and smoke.

Enclosures

D8103 Universal Enclosure
 D8108A Attack-resistant Enclosure
 D8109 Fire Enclosure

Magnetic Contacts

Bosch magnetic contacts include recessed, terminal connection, miniature, overhead door, and surface mount.

Modules

Conetix ITS-DX4020-G GPRS/GSM Integrated Communicator
 Conetix DX4020 Network Interface Module
 Conetix DX4010V2 USB/Serial Interface Module
 Conetix C900V2 Dialer Capture Module
 D113 Battery Lead Supervision Module
 D125B Dual Class B Initiating Module
 D127 Reversing Relay Module
 D129 Class A Initiating Module
 D130 Auxiliary Relay Module
 D185 Reverse Polarity Signaling Module
 D192G Notification Appliance Circuit Module
 D928 Phone Line Switcher
 D5060 MUX Programmer
 D8125 POPEX Point Expander
 D8128D OctoPOPIT Eight-point Expander
 D8125MUX Point Expander
 D8125INV Wireless Interface Module
 D8129 Octo-relay Module
 D8130 Door Release Module
 D9127 Series POPIT Modules

Modules

D9131A Parallel Printer Interface Module
 D9210BLC Access Control Interface Module
 DS7432 Eight-input Remote Module
 DS7457i Series Single-zone Multiplex Input Modules
 DS7460i Two-input Module
 DS7461i Single-input Multiplex Module
 DS7465i Input and Output Module
 ICP-SDI-9114 SDI Splitter

Programming

RPS or RPS-LITE Remote Programming Software

Readers

ARD-R10 iCLASS Mullion Reader
 ARD-R40 iCLASS Switchplate Reader
 ARD-RK40-09 iCLASS PIN Reader
 ARD-VSMART iCLASS Reader
 D8223 Prox Pro Reader
 D8224 Mullion Reader
 D8224-SP Switch Plate Reader
 D8225 Mini Mullion Reader
 D8301W Low-profile Proximity Readers

Commercial Wireless Products

ISW-D8125CW Commercial Wireless Interface
 ISW-EN7280 Serial Receiver
 ISW-EN4200 Serial Receiver
 ISW-EN4204R LED Receiver
 ISW-EN4216R LCD Receiver
 ISW-EN4016SK Survey Receiver
 ISW-EN5040-T High-power Repeater
 ISW-EN1210 Universal Transmitter (Single-input)
 ISW-EN1210EOL Universal Transmitter with EOL Resistor
 ISW-EN1210SK Survey Transmitter
 ISW-EN1210W Door-Window Transmitter with Reed Switch
 ISW-EN1215EOL Universal Transmitter with Wall Tamper and EOL Resistor
 ISW-EN1215WEOL Door-Window Transmitter with Wall Tamper, Reed Switch, and EOL Resistor
 ISW-EN1223D Water-resistant Pendant Transmitter (Double-button)
 ISW-EN1223S Water-resistant Pendant Transmitter (Single-button)
 ISW-EN1223SK Survey Pendant Transmitter
 ISW-EN1233D Necklace Pendant Transmitter (Double-button)
 ISW-EN1233S Necklace Pendant Transmitter (Single-button)
 ISW-EN1235D Beltclip Pendant Transmitter (Double-button)
 ISW-EN1235S Beltclip Pendant Transmitter (Single-button)
 ISW-EN1235DF Fixed-location Transmitter (Double-button)
 ISW-EN1235SF Fixed-location Transmitter (Double-button)
 ISW-EN1242 Smoke Detector-Transmitter

Commercial Wireless Products

ISW-EN1247 Glassbreak Sensor-Transmitter

ISW-EN1249 Billtrap Transmitter

ISW-EN1260 PIR Motion Sensor Transmitter (Commercial and High-end Domestic Applications)

ISW-EN1261HT PIR Motion Sensor Transmitter (High-traffic Areas)

ISW-EN1262 PIR Motion Sensor Transmitter (Residential and Low-traffic Commercial Applications)

ISW-EN1265 PIR Motion Sensor Transmitter (Ceiling-mount Applications)

Parts Included

The D9412GV3 includes the following parts:

Quant.	Component
1	D9412GV3 Board
1	Mounting Skirt
1	Faceplate with D9412GV3 Label
1	Literature pack <ul style="list-style-type: none"> • Installation Instructions • Owners Manual • Release Notes
1	Literature CD containing all product literature

The available kits come with the parts indicated in the following table:

Components	Kits		
	-A	-B	-C
D9412GV3 Board	1	1	1
D101F Lock and Key Set			1
D122 Dual Battery Harness		1	
D161 Dual Modular Phone Cord		2	
D928 Dual Phone Line Switcher		1	
D1640 Transformer		1	1
D8103 Enclosure			1
D8108A Attack-resistant Enclosure	1		
D8109 Fire Enclosure		1	

Technical Specifications

Communications

SDI Bus A (+): 9 VDC
4572 m (15,000 ft)

SDI Bus B (-): 9 VDC
4572 m (15,000 ft)

Telephone Connection:

- One telephone line
- D928 Dual Phone Line Module required for two telephone lines

Environmental Considerations

Relative Humidity: 5% to 93% at +30°C (+86°F), non-condensing

Temperature (Operating): 0°C to +50°C (+32°F to +122°F)

Number of...

Areas:	8
Card Readers (Doors):	8
Credentials (Tokens):	996
Custom Functions:	16
Events:	Up to 1000
Passcode Users:	249, plus 1 service passcode
Parallel Printers:	3
Points:	246 (8 on-board, up to 238 off-board)
Programmable Relay Outputs:	131
RF Points:	238
SKEDs:	64

Power Requirements

Current Draw (Maximum):	300 mA
Output (Alarm):	2 A at 12 VDC
Output (Auxiliary, Continuous Power, and Switched Auxiliary combined):	1.4 A at 12 VDC nominal
Voltage (Operating):	12 VDC nominal
Voltage (AC):	16.5 VAC 40 VA plug-in transformer (D1640)

Trademarks

Trademark names are used throughout this document. In most cases, these designations are claimed as trademarks or registered trademarks in one or more countries by their respective owners. Rather than placing a trademark symbol in every occurrence of a trademark name, Bosch Security Systems, Inc. uses the names only in an editorial fashion and to the benefit of the trademark owner with no intention of infringing the trademark.

Inovonics is a trademark of Inovonics Wireless Corporation.

Ordering Information**D9412GV3 Control Panel** **D9412GV3**

Includes one printed circuit board (PCB) with mounting skirt and faceplate with label, and a literature pack and CD.

D9412GV3-A Attack-resistant Package **D9412GV3-A**

Contains one PCB, one transformer, and one attack-resistant enclosure.

D9412GV3-B Fire/Burglar Package **D9412GV3-B**

Contains one PCB, one dual battery harness, two telephone cords, one telephone line switcher, one transformer, and one fire enclosure.

D9412GV3-C Standard Burglar Package **D9412GV3-C**

Contains one PCB, one lock and key set, one transformer, and one universal enclosure.

Accessories**ICP-SDI-9114 SDI Splitter** **ICP-SDI-9114**

Provides the ability to set up two independent SDI buses from a single SDI connection on the control panel.

D110 Tamper Switch **D110**

Screw-on tamper switch that fits all enclosures. Shipped in packages of two.

ICP-EZTS Dual Tamper Switch **ICP-EZTS**

Combination tamper switch with a wire loop for additional tamper outputs.

D8103 Enclosure **D8103**

Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).

D8108A Attack Resistant Enclosure **D8108A**

Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.). UL Listed. Includes lock and key set. Requires the D2402 Mounting Plate.

D8109 Fire Enclosure **D8109**

Red steel enclosure measuring 40.6 cm x 40.6 cm x 8.9 cm (16 in. x 16 in. x 3.5 in.). UL Listed. Includes a lock and key set.

D928 Dual Phone Line Switcher **D928**

Allows the control panel to operate over and supervise two separate phone lines. Only one D162 phone cord is supplied. Two additional D161 or D162 phone cords are required.

D122 Dual Battery Harness **D122**

Harness with circuit breaker. Connects two batteries to a compatible control panel.

D122L Dual Battery Harness with Long Leads **D122L**

Color-coded harness with circuit breaker and leads measuring 89 cm (35 in.). Connects 12 V batteries to compatible control panels.

Ordering Information**D126 Standby Battery (12 V, 7 Ah)** **D126**

Sealed lead-acid standby and auxiliary rechargeable power supply.

D1218 Battery (12 V, 18 Ah) **D1218**

A 12 V sealed lead-acid battery for standby and auxiliary power with two bolt-fastened terminals. Includes hardware for attaching battery leads or spade connectors

D1224 Battery (12 V, 26-28 Ah) **D1224**

A 12 V sealed lead-acid battery for standby and auxiliary power with two bolt-fastened terminals. Includes hardware for attaching battery leads or spade connectors.

D137 Mounting Bracket **D137**

Used to mount accessory modules in D8103, D8108A, and D8109 enclosures.

D138 Mounting Bracket, Right Angle **D138**

Used to mount accessory modules in D8103, D8108A, and D8109 enclosures.

D1640 Transformer **D1640**

System transformer rated at 16.5 VAC, 40 VA.

D8004 Transformer Enclosure **D8004**

For applications such as fire alarm that might require a transformer enclosure.

D9002-5 Mounting Skirt **D9002-5**

Mounts inside D8103, D8108A, and D8109 enclosures. Can accept up to six standard 7.62 cm x 12.7 cm (3 in. x 5 in.) cards.

D101 Lock and Key Set **D101**

Standard lock set with one key supplied. Uses the D102 (#1358) replacement key.

Software Options**RPS Kit (USB)** **D5500C-USB**

Account management and control panel-programming software with USB connection.

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: +31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6258 5511
Fax: +65 6571 2698
apr.securitysystems@bosch.com
www.boschsecurity.asia

Represented by